

Portable Energy Storage Power

Model : SRYG-2000

Product introduction

Features	2000WH Emergency power station
	Built in 2000WH /25.9V lithium battery
	AC100V1500W*2-4PCS , pure sine wave inverter output, peak power 3000W
	USB2.0 output 4PCS; Type-c 2pcs
	DC 12V output 2pcs ; Automobile cigarette lighter output Max 12V10A
	DC charge input 12V10A*1pc ; PV charge input 17-25V20A*1pc
	Wireless output 5V10W*2pcs
	AC and DC display
	Overload and over-temperature and short-circuit protection
	LED light 3w *2pcs (choosable)
DC switch /USE switch/Led switch/ AC switch/Wireless output switch	

Technical Parameters

Battery type and capacity	lithium battery 25.9V2000WH
Battery life times	more than 1500 times
Display	DC/AC voltage/load watt /Temperature and fault warning/Frequency and battery power
AC charging time	2pcs AC charge 8 hours can charge full
DC charge time	Use 100W18V panel 4pcs , 8 hours can charge full battery

Input:

PV charge-in	Max 36-50V20A , without panel (choosable)
DC charge-in	Max 29.4V20A , with 1 pc adaptor charge 29.4V5A
AC-in	without (choosable)

Output:

USB output	5V2A *4PCS ; Type-c 40W* 2pcs
Wireless output	5V10W*2PCS
DC output	Automobile cigarette lighter output Max 12V10A
	5.5*2.1mm DC output 12V5A*2PCS
AC output	220V/110V1500W* 4PCS 50/60HZ pure sine wave

Bluetooth player and FM	without (choosable)
LED lights	without (choosable)



PACKING

Each cart per set

Export packing	Product size (mm)	GIFT BOX	EXP CARTON
Length (mm)	384.0	424	434
Width (mm)	249.0	289	299
Height (mm)	290.0	330	340
Weight (Kg)	12.5	13.0	13.3